

# NSR0340V2

## Schottky Barrier Diode

Schottky barrier diodes are optimized for very low forward voltage drop and low leakage current and are used in a wide range of dc-dc converter, clamping and protection applications in portable devices. NSR0340V2 in a SOD-523 miniature package enables designers to meet the challenging task of achieving higher efficiency and meeting reduced space requirements.

### Features

- Very Low Forward Voltage Drop – 410 mV @ 100 mA
- Low Reverse Current – 0.5  $\mu$ A @ 25 V  $V_R$
- 250 mA of Continuous Forward Current
- Power Dissipation of 200 mW with Minimum Trace
- Very High Switching Speed
- Low Capacitance –  $C_T = 6$  pF
- This is a Pb-Free Device

### Typical Applications

- LCD and Keypad Backlighting
- Camera Photo Flash
- Buck and Boost dc-dc Converters
- Reverse Voltage and Current Protection
- Clamping & Protection

### Markets

- Mobile Handsets
- MP3 Players
- Digital Camera and Camcorders
- Notebook PCs and PDAs
- GPS

### MAXIMUM RATINGS

| Rating                                        | Symbol    | Value              | Unit |
|-----------------------------------------------|-----------|--------------------|------|
| Reverse Voltage                               | $V_R$     | 40                 | Vdc  |
| Forward Continuous Current (DC)               | $I_F$     | 250                | mA   |
| Non-Repetitive Peak Forward Surge Current     | $I_{FSM}$ | 1.0                | A    |
| ESD Rating: Human Body Model<br>Machine Model | ESD       | Class 2<br>Class A |      |

Stresses exceeding Maximum Ratings may damage the device. Maximum Ratings are stress ratings only. Functional operation above the Recommended Operating Conditions is not implied. Extended exposure to stresses above the Recommended Operating Conditions may affect device reliability.



**ON Semiconductor®**

<http://onsemi.com>

## 40 VOLT SCHOTTKY BARRIER DIODE



**SOD-523  
CASE 502**

### MARKING DIAGRAM



AD = Device Code  
M = Date Code\*  
▪ = Pb-Free Package

(Note: Microdot may be in either location)

\*Date Code orientation position may vary depending upon manufacturing location.

### ORDERING INFORMATION

| Device       | Package              | Shipping†          |
|--------------|----------------------|--------------------|
| NSR0340V2T1G | SOD-523<br>(Pb-Free) | 3000 / Tape & Reel |
| NSR0340V2T5G | SOD-523<br>(Pb-Free) | 8000 / Tape & Reel |

†For information on tape and reel specifications, including part orientation and tape sizes, please refer to our Tape and Reel Packaging Specifications Brochure, BRD8011/D.

# THERMAL CHARACTERISTICS

| Characteristic                                                                                           | Symbol                   | Max         | Unit                     |
|----------------------------------------------------------------------------------------------------------|--------------------------|-------------|--------------------------|
| Thermal Resistance<br>Junction-to-Ambient (Note 1)<br>Total Power Dissipation @ $T_A = 25^\circ\text{C}$ | $R_{\theta JA}$<br>$P_D$ | 600<br>200  | $^\circ\text{C/W}$<br>mW |
| Thermal Resistance<br>Junction-to-Ambient (Note 2)<br>Total Power Dissipation @ $T_A = 25^\circ\text{C}$ | $R_{\theta JA}$<br>$P_D$ | 300<br>400  | $^\circ\text{C/W}$<br>mW |
| Junction and Storage Temperature Range                                                                   | $T_J, T_{stg}$           | -55 to +150 | $^\circ\text{C}$         |

1. Mounted onto a 4 in square FR-4 board 10 mm sq. 1 oz. Cu 0.06" thick single-sided. Operating to steady state.
2. Mounted onto a 4 in square FR-4 board 1 in sq. 1 oz. Cu 0.06" thick single-sided. Operating to steady state.

# ELECTRICAL CHARACTERISTICS ( $T_A = 25^\circ\text{C}$ unless otherwise noted)

| Characteristic                                                                                        | Symbol   | Min | Typ               | Max               | Unit          |
|-------------------------------------------------------------------------------------------------------|----------|-----|-------------------|-------------------|---------------|
| Reverse Leakage<br>( $V_R = 10\text{ V}$ )<br>( $V_R = 25\text{ V}$ )<br>( $V_R = 40\text{ V}$ )      | $I_R$    |     | 0.2<br>0.5<br>1.5 | 1.0<br>3.0<br>6.0 | $\mu\text{A}$ |
| Forward Voltage<br>( $I_F = 10\text{ mA}$ )<br>( $I_F = 100\text{ mA}$ )<br>( $I_F = 200\text{ mA}$ ) | $V_F$    |     | 310<br>410<br>470 | 350<br>450<br>510 | mV            |
| Total Capacitance<br>( $V_R = 10\text{ V}, f = 1\text{ MHz}$ )                                        | CT       |     | 6.0               |                   | pF            |
| Reverse Recovery Time<br>( $I_F = I_R = 10\text{ mA}, I_R = 1.0\text{ mA}$ )                          | $t_{rr}$ |     | 5.0               |                   | ns            |






Figure 1. Recovery Time Equivalent Test Circuit


# NSR0340V2



**Figure 2. Forward Voltage**



**Figure 3. Leakage Current**



**Figure 4. Total Capacitance**

**onsemi**, **Onsemi**, and other names, marks, and brands are registered and/or common law trademarks of Semiconductor Components Industries, LLC dba "**onsemi**" or its affiliates and/or subsidiaries in the United States and/or other countries. **onsemi** owns the rights to a number of patents, trademarks, copyrights, trade secrets, and other intellectual property. A listing of **onsemi**'s product/patent coverage may be accessed at [www.onsemi.com/site/pdf/Patent-Marking.pdf](http://www.onsemi.com/site/pdf/Patent-Marking.pdf). **onsemi** reserves the right to make changes at any time to any products or information herein, without notice. The information herein is provided "as-is" and **onsemi** makes no warranty, representation or guarantee regarding the accuracy of the information, product features, availability, functionality, or suitability of its products for any particular purpose, nor does **onsemi** assume any liability arising out of the application or use of any product or circuit, and specifically disclaims any and all liability, including without limitation special, consequential or incidental damages. Buyer is responsible for its products and applications using **onsemi** products, including compliance with all laws, regulations and safety requirements or standards, regardless of any support or applications information provided by **onsemi**. "Typical" parameters which may be provided in **onsemi** data sheets and/or specifications can and do vary in different applications and actual performance may vary over time. All operating parameters, including "Typicals" must be validated for each customer application by customer's technical experts. **onsemi** does not convey any license under any of its intellectual property rights nor the rights of others. **onsemi** products are not designed, intended, or authorized for use as a critical component in life support systems or any FDA Class 3 medical devices or medical devices with a same or similar classification in a foreign jurisdiction or any devices intended for implantation in the human body. Should Buyer purchase or use **onsemi** products for any such unintended or unauthorized application, Buyer shall indemnify and hold **onsemi** and its officers, employees, subsidiaries, affiliates, and distributors harmless against all claims, costs, damages, and expenses, and reasonable attorney fees arising out of, directly or indirectly, any claim of personal injury or death associated with such unintended or unauthorized use, even if such claim alleges that **onsemi** was negligent regarding the design or manufacture of the part. **onsemi** is an Equal Opportunity/Affirmative Action Employer. This literature is subject to all applicable copyright laws and is not for resale in any manner.

## ADDITIONAL INFORMATION

### TECHNICAL PUBLICATIONS:

Technical Library: [www.onsemi.com/design/resources/technical-documentation](http://www.onsemi.com/design/resources/technical-documentation)  
onsemi Website: [www.onsemi.com](http://www.onsemi.com)

### ONLINE SUPPORT: [www.onsemi.com/support](http://www.onsemi.com/support)

For additional information, please contact your local Sales Representative at  
[www.onsemi.com/support/sales](http://www.onsemi.com/support/sales)